

## **Alexander Neo Series Preset Save and Restore**

### **Mac OS X:**

We can recommend the free program Snoize SysEx Librarian for the Mac, which is available for [download from this page](#).

### **How to receive the MIDI dump in SysEx Librarian:**

First, install SysEx Librarian and make sure that you have the appropriate MIDI connection between the unit and the Mac. To save the SysEx dump on the Mac, please do the following:

1. Launch SysEx Librarian.
2. Hold the center Select button on your Neo pedal and connect it to your PC. Release the Select button when the main LED turns violet.
3. Select your MIDI interface in the dropdown menu at the top (if it's not already selected)
4. Click the 'Record Many' button.
5. Hold the BYPASS footswitch on your Neo pedal to initiate the dump.
6. Press the 'Done' button.
7. When the dump is completed doubleclick the newly created file in the window and name it. It has automatically been saved to your home directory ( under /Users/<your name>/Documents/SysEx Librarian/ ).

### **How to send the data back to your unit:**

1. Launch SysEx Librarian.
2. Connect your Neo pedal to your computer with the USB cable.
3. Select your MIDI interface in the dropdown menu at the top - it should be called "Alexander MIDI."
4. Drag the MIDI SysEx file from the Finder into the frame of SysEx Librarian (if it's not already in there).
5. Select it with the mouse.
6. Click Play.

## **Windows.**

We can recommend the free program MIDI-OX for Windows, which is available for [download from this page](#).

### **How to receive the MIDI dump in MIDIOX:**

First, install MIDI-OX and make sure that you have the appropriate MIDI connection between the unit and your PC. To save the SysEx dump on your PC, please do the following:

1. Hold the center Select button on your Neo pedal and connect it to your PC. Release the Select button when the main LED turns violet.
2. Launch MIDI-OX
3. Choose View / Sysex
4. In the Sysex window, choose Sysex > Receive manual dump
5. Hold the BYPASS footswitch on your Neo pedal to start the dump
6. When the dump is completed, choose Display Window > Save as...

### **How to send the data back to your unit:**

1. Connect your Neo pedal to your computer with the USB cable.
2. Launch MIDI-OX
3. In the Sysex window, choose Command > Window > Load File and navigate the location where you stored the file.
4. Choose Command Window > Send Sysex